

# Esp32 - Lora



ESP32 (32 bits, 2 cores, 180 MHz)

- 1. -Connectivity
  - 1. -WiFi
  - 2. -BLE
  - 3. -LoRa (SX1276) 433MHz, 868MHz, 915MHz

## Brochage ESP32 Lora



## Liens web

[ESP32 WiFi LoRa](#)

[Diagram Pinout](#)

[Github](#)

## Configuration

Formatage automatique	⌘T
Archiver le croquis	
Réparer encodage & recharger	
Moniteur série	⌘M
Traceur série	⌘L
WiFi101 Firmware Updater	
ArduBlock	
Type de carte: "WiFi_Kit_32"	▶
Flash Frequency: "80MHz"	▶
Upload Speed: "921600"	▶
Port: "/dev/cu.SLAB_USBtoUART"	▶
Get Board Info	
Programmeur: "AVRISP mkII"	▶
Graver la séquence d'initialisation	

## Programmes

### Carte1 (envoi)

Ouvrer et televerser le programme : Exemples > LoRaLibrary > OLED\_LoRa\_Sender

### Carte 2 (Reception)

Ouvrer et televerser le programme : Exemples > LoRaLibrary > OLED\_LoRa\_Receiver

## Ajouter la configuration LoRaWAN

Ajoutez les déclarations suivantes dans les 2 programmes.

[Lorawanconf.ino](#)

```
...  
  
// LoRa API  
https://github.com/Heltec-Aaron-Lee/WiFi_Kit_series/blob/master/esp32/libraries/LoRa/API.md  
  
// LoRaWAN Parameters  
#define BAND 868100000 //you can set band here directly,e.g.  
868E6,915E6  
#define PABOOST false  
#define TXPOWER 14
```

```
#define SPREADING_FACTOR 12
#define BANDWIDTH 125000
#define CODING_RATE 5
#define PREAMBLE_LENGTH 8
#define SYNC_WORD 0x34

void configForLoRaWAN()
{
    LoRa.setTxPower(TXPOWER);
    LoRa.setSpreadingFactor(SPREADING_FACTOR);
    LoRa.setSignalBandwidth(BANDWIDTH);
    LoRa.setCodingRate4(CODING_RATE);
    LoRa.setPreambleLength(PREAMBLE_LENGTH);
    LoRa.setSyncWord(SYNC_WORD);
    LoRa.crc();
}

String loraCfg = "Cfg:";
void displayLoRaConfig(int x, int y){
    loraCfg =
        "fr " + String(BAND/1000000, DEC)
        + " sf" + String(SPREADING_FACTOR, DEC)
        + " bw" + String(BANDWIDTH/1000, DEC)
        + " cr" + String(CODING_RATE, DEC) + "/4";
    display.drawString(x, y, loraCfg);
    loraCfg =
        + " pr" + String(PREAMBLE_LENGTH, DEC)
        + " pw" + String(TXPOWER, DEC)
        + " sw" + String(SYNC_WORD, HEX)
        ;
    display.drawString(x, y+10, loraCfg);
}

...

// should be done before LoRa.begin
configForLoRaWAN();

if (!LoRa.begin(BAND, PABOOST)) {
    display.drawString(0, 0, "Starting LoRa failed!");
    display.display();
    while (1);
}
displayLoRaConfig(0,20);
display.drawString(0, 0, "LoRa Initial success!");

...

display.display();

...
```

Last  
update:  
2023/01/27 16:08 start:arduino:esp32b:lora <https://www.magenealogie.chanterie37.fr/www/fablab37110/doku.php?id=start:arduino:esp32b:lora&rev=1616593029>

---

From:  
<https://www.magenealogie.chanterie37.fr/www/fablab37110/> - **Castel'Lab le Fablab MJC de Château-Renault**

Permanent link:  
<https://www.magenealogie.chanterie37.fr/www/fablab37110/doku.php?id=start:arduino:esp32b:lora&rev=1616593029>

Last update: **2023/01/27 16:08**

